# L99 Display Issue – Screen Upgrade Guide

L99 keyboard · driver installation, firmware mode and screen upgrade

## Step 1 · Check the keyboard connection

Before we start, make sure the keyboard switch is set to OFF and that the keyboard is connected by cable. If you can type, you can move on. If you cannot type, press Fn + 4 to enter wired mode.

Then install the driver and click the "Keyboard Upgrade" button.






## Step 2 · Start the screen upgrade

After the keyboard has been upgraded, click "Screen Upgrade". You will see that the "Start" button is grey and cannot be clicked.




## Step 3 · Enter firmware mode

Press and hold Fn + Spacebar on the keyboard for 3 seconds to enter firmware mode. The keyboard light will turn off, and the "Start" button will light up. You can click "Start"

then.







## Step 4 · Finish and restart

When the upgrade is finished, remove the cable, restart the keyboard with the on/off switch, then reconnect the cable.


System Settings
AULA L99
Language
English
Automatic Start
Key Response Time
*Delay setting parameters for Level 2:
Wired: approximately 5-6 ms, 2.4GHz:
approximately 7-9 ms, Bluetooth:
approximately 15-16 ms.
Note: Parameters may vary due to
different devices and surrounding
environmental interference.
Different switch types may lead to key
chatter if the delay setting is too
low.
If key chatter occurs, please increase
the delay setting.
2 Level
Sleep Time
1min
Keyboard Upgrade
Screen Upgrade
Reset Keyboard
Factory Reset
L99
Start
OK
Disable Windows Key
Disable ALT + F4
Disable ALT + TAB